

## REFERENCE

### 2630-, 2631-, AND 2632-TYPE TELEPHONE SETS

### IDENTIFICATION

#### 1. GENERAL

1.01 This section contains information for 2630-, 2631-, and 2632-type telephone sets. These telephone sets (Fig. 1 and 2) are general purpose CALL DIRECTOR® type telephone sets equipped with a TOUCH-TONE® dial. The 2630- and 2631-type sets can be used with 1A, 1A1, 1A2, 6A, or 6B key telephone systems and 3-type (MD) or 4A speakerphone system. The 2632-type sets have the same application except they cannot be used with 1A KTS. All 2632-type sets are rated Manufacture Discontinued. All 2630- and 2631-type telephone sets except 2630DAMS1 and 2631DAMS1 are rated Manufacture Discontinued (MD).

1.02 This section is reissued to:

- Show the 2630DAM and 2631DAM telephone sets MD
- Add the new 2630DAMS1 and 2631DAMS1 telephone sets
- Revise Tables A through E, G, and H.

1.03 ♦The new S coded telephone sets are similar to the previous type telephone sets except they are equipped with a new line switch which breaks both the tip and ring side of the line. Previous type sets broke only the ring side of the line.♦

**Note:** When S coded telephone sets are used with speakerphone the (G) dial lead must be moved from terminal 12 to terminal 2 bypassing the d'e' line switch contacts.

1.04 Early models designated with a single letter code (C or D) are equipped with 598-, 599-, 656- or 657-type keys using a KS-type connector. ♦Later sets designated by a multiletter code (DA),

(DAM), and (DAMS1)♦ are equipped with 635-type keys using 508- or 509-type plugs. The 598- and 599-type keys are electrically and mechanically interchangeable with the 656- and 657-type. None of these keys, however, are compatible with the 635-type keys and cannot be intermixed.

1.05 Nonmodular (single and double letter code) sets were furnished equipped with a G3-type handset and cord. All modular sets are furnished with a G15A handset, H4DU cord, and 616E jack assembly.



Fig. 1—♦Typical Modular Telephone Set Using 635-Type Keys♦

#### 2. IDENTIFICATION

##### 2.01 Table Index:

Table A—Replaceable Common Components

Table B—Coordinated Color Scheme

Table C—Housing Part Numbers

#### NOTICE

Not for use or disclosure outside the  
Bell System except under written agreement



Fig. 2—Typical Nonmodular Telephone Set Using 590 or 650 Series Keys

Table D—2630-Type Telephone Sets—Key Arrangement, Faceplate, and Bezel Components

Table E—2631-Type Telephone Sets—Key Arrangement, Faceplate, and Bezel Components

Table F—Manufacture Discontinued 2632-Type Telephone Sets—Key Arrangement, Faceplate, and Bezel Components

Table G—2630DAM and DAMS1 (18-button) Telephone Set—Key Module and Faceplate Arrangements

Table H—2631DAM and DAMS1 (30-Button) Telephone Set—Key Module and Faceplate Arrangements

Table I—Manufacture Discontinued 2630- and 2632-Type (18-button) Telephone Set—Key Module and Faceplate Arrangements

Table J—Manufacture Discontinued 2631-Type (30-Button) Telephone Set—Key Module and Faceplate Arrangements

2.02 A guard assembly (polarity guard) should be used with these sets when specified by local instructions to eliminate the affect of battery reversals in end-to-end signaling applications.

2.03 Current production telephone sets are equipped with a satin-silver (-87) mounting cord.

2.04 Current production telephone sets are factory-equipped with a KS-20419L1 (10 volt ac only) buzzer. Provisions are made for mounting a KS-8109L2 buzzer when an additional buzzer is desired.

2.05 Supplementary hold can be supplied in these sets as follows:

- **I hold**—Rewire existing hold key
- **Priority hold**—If equipped with a 599- or 657-type key in first module, replace with 599H or 657L. If equipped with a 635A5C or 635AD5C key in first module, replace key in **second** module with a 635A5C key. For wiring changes refer to the Service section for set involved.

2.06 The 2630D, 2631D, and 2632C sets are adaptable for use by a blind attendant with the addition of an 812263325 (P-22F332) retainer and guide assembly to each key.

2.07 For connection information, refer to Section 502-612-401. For additional installation and maintenance information refer to Section 502-600-100.

2.08 For use with 4A speakerphone system, refer to Section 512-730-400 for necessary wiring changes and connections.

2.09 Ordering Guide:

- 2630DAMS1-\*
- 2631DAMS1-\*

2.10 All single, double, and triple letter coded telephone sets are MD. The 2630DAMS1 or 2631DAMS1 set may be equipped with different module key arrangement. These sets will accommodate 635-type keys, 76A lamp sockets and/or 679A (MD) transmitter which must be ordered separately and field installed. Refer to Tables D and E for faceplate and key arrangements and to Tables G and H for faceplate and key module arrangement.

2.11 These sets are supplied with faceplate assemblies which consist of a faceplate and three mats; one each in silver (-78), gold (-79), and the coordinated color (Table B).

\*Complete code by adding color suffix (Table B).

◆ TABLE A ◆

## REPLACEABLE COMMON COMPONENTS

| SET CODE    | HANDSET CORD | HANDSET (NOTE 1) | DIAL    | RINGER (NOTE 2) | MTG CORD  | BEZEL FACEPLATE AND MAT | HOUSING |
|-------------|--------------|------------------|---------|-----------------|-----------|-------------------------|---------|
| 2630D(MD)   | H4CJ-*       | G3A6-*           | 35AF3A  | N1A or T1A      | D120C-87  | Table D                 | Table C |
| 2630DA(MD)  |              |                  |         |                 |           |                         |         |
| 2630DAM(MD) | H4DU-*       | G15A-*           |         |                 | D120M-87  |                         |         |
| 2630DAMS1   |              |                  |         |                 |           |                         |         |
| 2631D(MD)   | H4CJ-*       | G3A6-*           |         |                 | D200F-87  | Table E                 |         |
| 2631DA(MD)  |              |                  |         |                 |           |                         |         |
| 2631DAM(MD) | H4DU-*       | G15A-*           |         |                 | D200AA-87 |                         |         |
| 2631DAMS1   |              |                  |         |                 |           |                         |         |
| 2632C(MD)   | H4CJ-*       | G3A6-*           | D94B-87 | Table F         |           |                         |         |

Note 1: The G3A6 replaces the G3A4. These handsets differ only in the code in which the last numeral indicates the length of the cord.

Note 2: The T1A ringer can be used as a maintenance replacement for the N1A.

\* Add color suffix from Table B.

◆ TABLE B ◆

## COORDINATED COLOR SCHEME

| HANDSET, HANDSET CORD, MTG. CORD * COLOR | COLOR SUFFIX | FACEPLATE ASSY AND COORDINATED MAT COLOR | COLOR SUFFIX |
|--|--------------|--|--------------|
| Black                                    | (-03)        | Charcoal                                 | (-70)        |
| Green                                    | (-51)        | Lt. Green                                | (-71)        |
| Yellow                                   | (-56)        | Lt. Yellow                               | (-72)        |
| White                                    | (-58)        | Lt. Gray                                 | (-73)        |
| Lt. Beige                                | (-60)        | Muted Beige                              | (-75)        |
| Aqua Blue                                | (-62)        | Muted Blue                               | (-76)        |
| Any Color Set                            | —            | Silver                                   | (-78)        |
|  |              | Gold                                     | (-79)        |

\* Mounting cords in all colors are MD except for satin-silver (-87).

◆ TABLE C ◆

## HOUSING PART NUMBERS

| COLOR     | 2630D                   | 2630DA    | 2630DAM<br>2630DAMS1 | 2631D                   | 2631DA    | 2631DAM<br>2631DAMS1 | 2632C                   |
|-----------|-------------------------|-----------|----------------------|-------------------------|-----------|----------------------|-------------------------|
| Black     | 818430035<br>(P-84C003) | 840471031 | 840712012            | 818431033<br>(P-84C103) | 840472039 | 840712269            | 818430035<br>(P-84C003) |
| Green     | 818430514<br>(P-84C051) | 840471510 | 840712020            | 818431512<br>(P-84C151) | 840472518 | 840712277            | 818430514<br>(P-84C051) |
| Yellow    | 818430563<br>(P-84C056) | 840471569 | 840712038            | 818431561<br>(P-84C156) | 840472567 | 840712285            | 818430563<br>(P-84C056) |
| White     | 818430589<br>(P-84C058) | 840471585 | 840712046            | 818431587<br>(P-84C158) | 840472583 | 840712293            | 818430589<br>(P-84C058) |
| Lt. Beige | 818430605<br>(P-84C060) | 840471601 | 840712053            | 818431603<br>(P-84C160) | 840472609 | 840712301            | 818430605<br>(P-84C060) |
| Aqua Blue | 818430621<br>(P-84C062) | 840471627 | 840712061            | 818431629<br>(P-84C162) | 840472625 | 840712319            | 818430621<br>(P-84C062) |

◆ TABLE D ◆

## 2630-TYPE TELEPHONE SET—KEY ARRANGEMENT, FACEPLATE, AND BEZEL COMPONENTS

| TEL SET CODE | KEY ARRANGEMENT |            |            | FACEPLATE ASSEMBLY† (NOTE 1) | FACEPLATE ONLY | PAPER MATS   |                         |                         | BEZEL RETAINER GROUP (NOTE 2) |           |  |                         |                         |
|--------------|-----------------|------------|------------|------------------------------|----------------|--|-------------------------|-------------------------|-------------------------------|-----------|--|-------------------------|-------------------------|
|              | 1ST MODULE      | 2ND MODULE | 3RD MODULE |                              |                | COORDINATED COLOR  | SILVER                  | GOLD                    |                               |           |  |                         |                         |
| D1*          | 599A            | 598A       | 105B       | 220A1                        | 840149233      | 818380032 (P-83H003)<br>818380511 (P-83H051)<br>818380560 (P-83H056)<br>818380586 (P-83H058)<br>818380602 (P-83H060)<br>818380628 (P-83H062) | 818380784<br>(P-83H078) | 818380792<br>(P-83H079) | 814455085<br>(P-44E508)       |           |  |                         |                         |
| D2*          |                 |            | 598A       |                              |                |  |                         |                         |                               |           |  |                         |                         |
| D4*          |                 |            | 617A       | 220B1                        | 840149231      |  |                         |                         |                               |           |  |                         |                         |
| D6*          | 599B            |            | 105B       | 220A1                        | 840149223      |  |                         |                         |                               |           |  |                         |                         |
| D7*          |                 |            | 598A       |                              |                |  |                         |                         |                               |           |  |                         |                         |
| D9*          | 598A            |            | 105B       |                              |                |  |                         |                         |                               |           |  |                         |                         |
| D10*         |                 |            | 598A       |                              |                |  |                         |                         |                               |           |  |                         |                         |
| D11*         | 599A            |            | 617A       |                              | 220C1          |  |                         |                         |                               | 840149249 | 818381030 (P-83H103)<br>818381519 (P-83H151)<br>818381568 (P-83H156)<br>818381584 (P-83H158)<br>818381600 (P-83H160)<br>818381626 (P-83H162) | 818381782<br>(P-83H178) | 818381790<br>(P-83H179) |
| D12*         |                 |            |            | 667B                         | 220D1          |  |                         |                         |                               | 840149256 |  |                         |                         |
| D13*         |                 |            |            |                              | 220C1          |  |                         |                         |                               | 840149249 |  |                         |                         |
| D14*         |                 | 598A       | 59A        | 220J1                        | 840149298      | Same as D1 thru D10  | 818380784<br>(P-83H078) | 818380792<br>(P-83H079) |                               |           |  |                         |                         |
| D15*         | 599B            |            |            |                              |                |  |                         |                         |                               |           |  |                         |                         |

\* MD

† Consists of faceplate and three paper mats — one each of the coordinated color, silver and gold.

◆ TABLE D (Contd) ◆

2630-TYPE TELEPHONE SET—KEY ARRANGEMENT, FACEPLATE, AND BEZEL COMPONENTS

| TEL SET CODE      | KEY ARRANGEMENT |            |            | FACEPLATE ASSEMBLY† (NOTE 1) | FACEPLATE ONLY          | PAPER MATS   |                         |                         | BEZEL RETAINER GROUP (NOTE 21) |
|-------------------|-----------------|------------|------------|------------------------------|-------------------------|--|-------------------------|-------------------------|--------------------------------|
|                   | 1ST MODULE      | 2ND MODULE | 3RD MODULE |                              |                         | COORDINATED COLOR  | SILVER                  | GOLD                    |                                |
| DA1/DAM1*         | 635A5C          | 635G5C     | 111B       | 220R1 (MD)<br>(Notes 4,5)    | 802697045<br>(P-269704) | 828336032 (P-83L603)<br>828336511 (P-83L651)<br>828336560 (P-83L656)<br>828336586 (P-83L658)<br>828336602 (P-83L660)<br>828336628 (P-83L662) | 828336784<br>(P-83L678) | 828336792<br>(P-83L679) | 814455085<br>(P-44E508)        |
| DA2/DAM2*         |                 |            | 635G5C     |                              |                         |  |                         |                         |                                |
| DA4/DAM4*         |                 |            | 658A       |                              |                         |  |                         |                         |                                |
| DA6/DAM6*         |                 |            | 111B       |                              |                         |  |                         |                         |                                |
| DA7/DAM7*         |                 |            | 635G5C     |                              |                         |  |                         |                         |                                |
| DA11/DAM11*       | 635A5C          | 658A       | 679A       | 220S1                        | 802697052<br>(P-269705) | 828337030 (P-83L703)<br>828337519 (P-83L751)<br>828337568 (P-83L756)<br>828337584 (P-83L758)<br>828337600 (P-83L760)<br>828337626 (P-83L762) | 828337782<br>(P-83L778) | 828337790<br>(P-83L779) |                                |
| DA12/DAM12*       |                 |            |            |                              |                         |  |                         |                         |                                |
| DA13/DAM13*       | 635AD5C         | 635G5C     | 76A        | 220R1 (MD)<br>(Notes 4,5)    | 802697045<br>(P-269704) | Same as DA1/DAM1<br>thru DA7/DAM7  | 828336784<br>(P-83L678) | 828336792<br>(P-83L679) |                                |
| DA14/DAM14*       | 635A5C          |            |            |                              |                         |  |                         |                         |                                |
| DA15/DAM15*       | 635AD5C         |            |            |                              |                         |  |                         |                         |                                |
| DAMS1<br>(Note 3) | 635A5C          | 635G5C     | 111B       |                              | 2620A<br>(Note 5)       |  |                         |                         |                                |

Note 1. Add color suffix from Table B.

Note 2. Consists of 814455051 (P-44E505) upper bezel, 814455069 (P-44E506) lower bezel, 814455077 (P-44E507) bezel retainer, 997126610 (RM-712661) bezel clip, and 997126628 (RM-712662) bezel spring.

Note 3. The DAMS1 telephone sets can be field converted to any of the above DAM code key configurations by ordering the keys separately.

Note 4. Early production sets are equipped with 220R1 (MD) faceplate assembly and 802697045 (P-269704) bezel assembly. The 2620A faceplate can be substituted for replacement purposes.

Note 5. Faceplate consists of a single piece snap-in textured faceplate. Code number must be suffixed with coordinate color number (Table B). Faceplate does not require the use of a bezel assembly.

\* MD

† Consists of faceplate and three paper mats — one each of the coordinated color, silver and gold.

◆ TABLE E ◆

## 2631-TYPE TELEPHONE SETS—KEY ARRANGEMENTS, FACEPLATE, AND BEZEL COMPONENTS

| TEL SET CODE | KEY ARRANGEMENT |            |                         |                         |            | FACEPLATE ASSEMBLY† (NOTE 1) | FACEPLATE ONLY | PAPER MATS   |                         |                         | BEZEL ASSEMBLY          |  |                         |                         |
|--------------|-----------------|------------|-------------------------|-------------------------|------------|------------------------------|----------------|--|-------------------------|-------------------------|-------------------------|--|-------------------------|-------------------------|
|              | 1ST MODULE      | 2ND MODULE | 3RD MODULE              | 4TH MODULE              | 5TH MODULE |                              |                | COORDINATED COLOR  | SILVER                  | GOLD                    |                         |  |                         |                         |
| D1*          | 599A            | 598A       | 598A                    | 105B                    | 105B       | 221A1                        | 840149306      | 818480030 (P-84H003)<br>818480519 (P-84H051)<br>818480568 (P-84H056)<br>818480584 (P-84H058)<br>818480600 (P-84H060)<br>818480626 (P-84H062) | 818480782<br>(P-84H078) | 818480790<br>(P-84H079) | 812652121<br>(P-26E212) |  |                         |                         |
| D2*          |                 |            |                         | 105B                    |            |                              |                |  |                         |                         |                         |  |                         |                         |
| D3*          |                 |            |                         | 598A                    | 598B       |                              |                |  |                         |                         |                         |  |                         |                         |
| D4*          |                 |            |                         | 617A                    | 221B1      | 840149314                    |                |  |                         |                         |                         |  |                         |                         |
| D5*          |                 |            |                         | 617A                    | 221E1      | 840149348                    |                |  |                         |                         |                         |  |                         |                         |
| D9*          | 105B            |            |                         | 59A                     | 221F1      | 840149355                    |                |  |                         |                         |                         |  |                         |                         |
| D10*         | 599B            |            |                         | 105B                    | 105B       | 221A1                        | 840149306      |  |                         |                         |                         |  |                         |                         |
| D11*         |                 |            |                         | 598A                    | 598A       |                              |                |  |                         |                         |                         |  |                         |                         |
| D12*         |                 |            |                         | 598A                    | 598A       |                              |                |  |                         |                         |                         |  |                         |                         |
| D13*         | 598A            |            |                         | 105B                    | 105B       | 221A1                        | 840149306      |  |                         |                         |                         |  |                         |                         |
| D14*         |                 |            |                         | 598A                    | 598A       |                              |                |  |                         |                         |                         |  |                         |                         |
| D15*         |                 |            |                         | 598A                    | 598A       |                              |                |  |                         |                         |                         |  |                         |                         |
| D16*         | 599A            |            |                         | 105B                    | 667B       | 221C1                        | 840149322      |  |                         |                         |                         | 818481038 (P-84H103)<br>818481517 (P-84H151)<br>818481566 (P-84H156)<br>818481582 (P-84H158)<br>818481608 (P-84H160)<br>818481624 (P-84H162) | 818481780<br>(P-84H178) | 818481798<br>(P-84H179) |
| D17*         |                 |            |                         | 598A                    |            | 221D1                        | 840149330      |  |                         |                         |                         |  |                         |                         |
| D18*         |                 |            |                         | 617A                    | 59A        | 221F1                        | 840149355      |  |                         |                         |                         | Same as D1 thru D15  |                         |                         |
| D19*         |                 | 598A       | 818480782<br>(P-84H078) | 818480790<br>(P-84H079) |            |                              |                |  |                         |                         |                         |  |                         |                         |

\* MD.

† Consists of faceplate and three mats — one each of the coordinated color, silver and gold.

◆ TABLE E (Contd) ◆

2631-TYPE TELEPHONE SETS—KEY ARRANGEMENTS, FACEPLATE, AND BEZEL COMPONENTS

| TEL SET CODE      | KEY ARRANGEMENT |            |            |            |            | FACEPLATE ASSEMBLY† (NOTE 1) | FACEPLATE ONLY          | PAPER MATS   |                         |                         | BEZEL ASSEMBLY        |     |
|-------------------|-----------------|------------|------------|------------|------------|------------------------------|-------------------------|--|-------------------------|-------------------------|-----------------------|-----|
|                   | 1ST MODULE      | 2ND MODULE | 3RD MODULE | 4TH MODULE | 5TH MODULE |                              |                         | COORDINATED COLOR  | SILVER                  | GOLD                    |                       |     |
| DA1/DAM1*         | 635A5C          | 635G5C     | 635G5C     | 111B       | 111B       | 221R1 (MD)<br>(Notes 4, 5)   | 802697060<br>(P-269706) | 828430033 (P-84L003)<br>828430512 (P-84L051)<br>828430561 (P-84L056)<br>828430587 (P-84L058)<br>828430603 (P-84L060)<br>828430629 (P-84L062) | 828430785<br>(P-84L078) | 828430793<br>(P-84L079) | 840155642<br>(Note 2) |     |
| DA2/DAM2*         |                 |            |            |            |            |                              |                         |  |                         |                         |                       |     |
| DA3/DAM3*         |                 |            |            | 635G5C     | 635G5C     |                              |                         |  |                         |                         |                       |     |
| DA4/DAM4*         |                 |            |            |            | 658A       |                              |                         |  |                         |                         |                       |     |
| DA5/DAM5*         |                 |            |            | 658A       | 76A        |                              |                         |  |                         |                         |                       |     |
| DA9/DAM9*         |                 |            |            | 111B       |            |                              |                         |  |                         |                         |                       |     |
| DA10/DAM10*       | 635AD5C         | 635G5C     | 635G5C     |            | 111B       | 221S1                        | 802697078<br>(P-269707) | 828431031 (P-84L103)<br>828431601 (P-84L151)<br>828431569 (P-84L156)<br>828431585 (P-84L158)<br>828431601 (P-84L160)<br>828431627 (P-84L162) | 828431783<br>(P-84L178) | 828431791<br>(P-84L179) |                       |     |
| DA11/DAM11*       |                 |            |            | 635G5C     |            |                              |                         |  |                         |                         |                       |     |
| DA12/DAM12        |                 |            |            |            | 635G5C     |                              |                         |  |                         |                         |                       |     |
| DA16/DAM16*       | 635A5C          | 635G5C     | 635G5C     | 111B       | 679A       | 221S1                        | 802697078<br>(P-269707) | 828431031 (P-84L103)<br>828431601 (P-84L151)<br>828431569 (P-84L156)<br>828431585 (P-84L158)<br>828431601 (P-84L160)<br>828431627 (P-84L162) | 828431783<br>(P-84L178) | 828431791<br>(P-84L179) |                       |     |
| DA17/DAM17*       |                 |            |            | 635G5C     |            |                              |                         |  |                         |                         |                       |     |
| DA18/DAM18*       |                 |            |            | 658A       |            |                              |                         |  |                         |                         |                       |     |
| DA19/DAM19*       |                 |            |            | 635G5C     |            |                              |                         |  |                         |                         |                       | 76A |
| DAMS1<br>(Note 3) | 635A5C          | 635G5C     | 635G5C     | 111B       | 111B       |                              | 2621A<br>(Note 5)       |  |                         |                         |                       |     |

Note 1. Add color suffix from Table B.

Note 2. Consists of 834089939 (P-40Y093) upper bezel, 834080947 (P-40Y094) lower bezel, 814455077 (P-44E507) bezel retainer, 997126610 (RM-742861) bezel clip, and 997126628 (RM-712662) bezel spring.

Note 3. The DAMS1 telephone sets can be field converted to any of the above DAM code key configurations by ordering the keys separately.

Note 4. Early production sets are equipped with 221R1 (MD) faceplate assembly and 802697060 (P-269706) bezel assembly. The 2621A faceplate can be substituted for replacement purposes.

Note 5. Faceplate consists of a single piece snap-in textured faceplate. Code number must be suffixed with coordinated color number (Table B). Faceplate does not require the use of a bezel assembly.

† Consists of faceplate and three paper mats – one each of the coordinated color, silver and gold.



◆ TABLE F ◆  
**MANUFACTURE DISCONTINUED 2632-TYPE TELEPHONE SETS—KEY ARRANGEMENT, FACEPLATE, AND BEZEL COMPONENTS**

| TEL SET CODE * | KEY ARRANGEMENT |            |            | FACE-PLATE ASSY † (NOTE 1) | FACEPLATE ONLY | PAPER MATS   |                         |                         | BEZEL RETAINER GROUP (NOTE 2) |
|----------------|-----------------|------------|------------|----------------------------|----------------|--|-------------------------|-------------------------|-------------------------------|
|                | 1ST MODULE      | 2ND MODULE | 3RD MODULE |                            |                | COORDINATED COLOR  | SILVER                  | GOLD                    |                               |
| C1             | 599A            | 598A       | 105B       | 220A1                      | 840149223      | 818380032 (P-83H003)<br>818380511 (P-83H051)<br>818380560 (P-83H056)<br>818380586 (P-83H058)<br>818380602 (P-83H060)<br>818380628 (P-83H062) | 818380784<br>(P-83H078) | 818380792<br>(P-83H079) | 814455085<br>(P-44E508)       |
| C2             | 599A            | 598A       | 598A       |                            |                |  |                         |                         |                               |
| C4             | 599A            | 598A       | 617A       | 220B1                      | 840149231      |  |                         |                         |                               |
| C6             | 599B            | 598A       | 105A       | 220A1                      | 840149223      |  |                         |                         |                               |
| C7             | 599B            | 598A       | 598A       |                            |                |  |                         |                         |                               |
| C11            | 599A            | 598A       | 667B       | 220C1                      | 840149249      | 818381030 (P-83H103)<br>818381519 (P-83H151)<br>818381568 (P-83H156)<br>818381584 (P-83H158)<br>818381600 (P-83H160)<br>818381626 (P-83H062) | 818381782<br>(P-83H178) | 818381790<br>(P-83H179) |                               |
| C12            | 599A            | 617A       | 667B       | 220D1                      | 840149256      |  |                         |                         |                               |
| C13            | 599B            | 598A       | 667B       | 220C1                      | 840149249      |  |                         |                         |                               |
| C14            | 599A            | 598A       | 59A        | 220J1                      | 840149298      |  |                         |                         |                               |
| C15            | 599B            | 598A       | 59A        |                            |                |  |                         |                         |                               |

\* All 2632-type telephone sets are MD.

† Consists of faceplate and three paper mats—one each each of the coordinated color, silver and gold.

Note 1: Add color suffix from Table B.

Note 2: Consists of 814455051 (P-44E505) upper bezel, 814455069 (P-44E506) lower bezel, 814455077 (P-44E507) bezel retainer, 997126610 (RM-712661) bezel clip, and 997126628 (RM-712662) bezel spring.

◆ TABLE G ◆

**2630DAM AND DAMS1 (18-BUTTON) TELEPHONE SETS—KEY MODULE  
AND FACEPLATE ARRANGEMENTS (NOTES)**

| TEL SET CODE                                | FACEPLATE PART NUMBER                   | KEY CONFIGURATION AND CODES (NOTE 1)                   |   |  |  |
|---|---|--|---|--|--|
| 2630DAM1(MD),<br>2(MD), 6(MD),<br>and 7(MD) | 802697045<br>(P-269704)<br>(Notes 4, 5) | PPB<br>PPB<br>PPB (1)<br>PPB<br>PPB<br>HPB             | PPP<br>PPP<br>PPP (2)<br>PPP<br>PPP<br>HPP        | PPB<br>PPB<br>PPB (6)<br>PPB<br>CPB<br>HPB | PPP<br>PPP<br>PPP (7)<br>PPP<br>CPP<br>HPP |
| 2630DAM4(MD)                                |   | PPSS<br>PPSS<br>PPSS (4)<br>PPSS<br>HPSS               |   |  |  |
| 2630DAM11(MD)<br>and 13(MD)<br>(Note 2)     | 802697052<br>(P-269705)<br>(Notes 4, 5) | PP OFF<br>PP ON<br>PP T (11)<br>PP V<br>PP<br>HP       | PP OFF<br>PP ON<br>PP T (13)<br>PP V<br>CP<br>HP  |  |  |
| 2630DAM12(MD)<br>(Note 2)                   |   | PSS OFF<br>PSS ON<br>PSS T (12)<br>PSS V<br>PSS<br>HSS |   |  |  |
| 2630DAM14(MD)<br>and 15 (MD)                | 802697045<br>(P-269704)<br>(Note 4, 5)  | PPLL<br>PPLL<br>PPLL (14)<br>PPLL<br>HPLL              | PPLL<br>PPLL<br>PPLL (15)<br>PPLL<br>CPLL<br>HPLL |  |  |
| 2630DAMS1<br>(Note 3)                       | 2620A<br>(Note 5)                       | PPB<br>PPB<br>PPB<br>PPB<br>PPB<br>HPB                 |   |  |  |

*Note 1.* Numerals in parenthesis indicate code of set.

*Note 2.* Key module arrangements apply to 3-type speakerphone only. For use with 4A speakerphone, refer to Section 512-730-400.

*Note 3.* The DAMS1 telephone sets can be field converted to any of the DAM code, key configurations by ordering the keys separately.

*Note 4.* Early production sets are equipped with 220R1 (MD) faceplate assembly and 802597060 (P-269706) bezel assembly. The 2620A faceplate can be substituted for replacement purposes.

*Note 5.* Faceplate consists of a single piece snap-in textured faceplate. Code number must be suffixed with coordinated color number (Table B). Faceplate does not require the use of a bezel assembly.

*Symbols:*

P — Pickup (locking)  
H — Hold  
C — Cutoff (turn-locking)  
SS — Signal  
B — Blank

T — Transmitter  
V — Volume Control  
LL — Illuminating Lamp  
OFF — OFF  
ON — ON

◆ TABLE H ◆

2631DAM AND DAMS1 (30-BUTTON) TELEPHONE SET-KEY MODULE AND FACEPLATE ARRANGEMENTS (NOTES)

| TELSET CODE                             | FACEPLATE PART NUMBER                   | KEY CONFIGURATION (NOTE 1)   |  |  |   |   |   |   |  |
|---|---|--|--|--|---|---|---|---|--|
| 2631DAM1(MD)                            | 802697060<br>(P-269706)<br>(Note 4, 5)  | PPPBB<br>PPPBB<br>PPPBB (1)<br>PPPBB<br>PPPBB<br>HPPBB             | PPPPB<br>PPPPB<br>PPPPB (2)<br>PPPPB<br>PPPPB<br>HPPPB       | PPPPP<br>PPPPP<br>PPPPP (3)<br>PPPPP<br>PPPPP<br>HPPPP | PPPBB<br>PPPBB<br>PPPBB (10)<br>PPPBB<br>CPPBB<br>HPPBB | PPPPB<br>PPPPB<br>PPPPB (11)<br>PPPPB<br>CPPPB<br>HPPPB | PPPPP<br>PPPPP<br>PPPPP (12)<br>PPPPP<br>CPPPP<br>HPPPB | PPPBB<br>PPPBB<br>PPPBB (13)<br>PPPBB<br>PPPBB<br>PPPBB |  |
| 2631DAM4(MD)                            |   | PPPPSS<br>PPPPSS<br>PPPPSS (4)<br>PPPPSS<br>HPPSS                  |  |  |   |   |   |   |  |
| 2631DAM16(MD)<br>and 17(MD)<br>(Note 2) | 802697078<br>(P-269707)<br>(Note 4, 5)  | PPPBB OFF<br>PPPBB ON<br>PPPBB T (16)<br>PPPBB V<br>PPPBB<br>HPPBB | PPPP OFF<br>PPPP ON<br>PPPP T (17)<br>PPPP V<br>PPPP<br>HPPP |  |   |   |   |   |  |
| 2631DAM18(MD)<br>(Note 2)               |   | PPSS OFF<br>PPSS ON<br>PPSS T (18)<br>PPSS V<br>PPSS<br>HPPSS      |  |  |   |   |   |   |  |
| 2631DAM5(MD)                            | 802697060<br>(P-269706)<br>(Notes 4, 5) | PPSSLL<br>PPSSLL<br>PPSSLL (5)<br>PPSSLL<br>HPPSSLL                |  |  |   |   |   |   |  |
| 2631DAM9(MD)<br>and 19(MD)              |   | PPBLL<br>PPBLL<br>PPBLL (9)<br>PPBLL<br>HPPBLL                     | PPPLL<br>PPPLL<br>PPPLL (19)<br>PPPLL<br>HPPPLL              |  |   |   |   |   |  |

◆ TABLE H (Contd) ◆

2631DAM AND DAMS1 (30-BUTTON) TELEPHONE SET—KEY MODULE AND FACEPLATE ARRANGEMENTS (NOTES)

| TELSET CODE            | FACEPLATE PART NUMBER | KEY CONFIGURATION (NOTE 1)                         |
|------------------------|-----------------------|--|
| 2631DAMS1<br>(Note -3) | 2621A<br>(Note 5)     | PPPBB<br>PPPBB<br>PPPBB<br>PPPBB<br>PPPBB<br>HPPBB |

*Note 1.* Numerals in parenthesis indicate code of set.

*Note 2.* Key module arrangements apply to 3-type speakerphone only. For use with 4A speakerphone, refer to Section 512-730-400.

*Note 3.* The DAMS1 telephone sets can be field converted to any of the DAM code, key configurations by ordering the keys separately.

*Note 4.* Early production sets are equipped with 221R1(MD) faceplate assembly and 802697060 (P-269706) bezel assembly. The 2621A faceplate can be substituted for replacement purposes.

*Note 5.* Faceplate consists of a single piece snap-in textured faceplate. Code number must be suffixed with coordinated color number (Table -B). Faceplate does not require the use of a bezel assembly.

**Symbols:**

P — Pickup (locking)  
 H — Hold  
 C — Cutoff (turn-locking)  
 SS — Signal  
 B — Blank

T — Transmitter  
 V — Volume Control  
 LL — Illuminating Lamp  
 OFF — OFF  
 ON — ON

♦ TABLE I ♦  
 MANUFACTURED DISCONTINUED 2630- AND 2632-TYPE (18-BUTTON) TELEPHONE SET—KEY MODULE AND  
 FACEPLATE ARRANGEMENTS (NOTES)

| TEL SET<br>CODE*  | KEY CONFIGURATION AND CODES (NOTE 1)                   |   |   |   |   |  |
|---|--|---|---|---|---|--|
| 2630B1, 2, 6, 7, 9, 10<br>2630C1, 2, 6, 7, 9, 10<br>2630D1, 2, 6, 7, 9, 10<br>2630DA1, 2, 6, 7<br>2632A1, 2, 6, 7, 9, 10<br>2632C1, 2, 6, and 7 | PPB<br>PPB<br>PPB<br>PPB<br>PPB<br>HPB                 | PPP<br>PPP<br>PPP<br>PPP (2)<br>PPP<br>HPP        | CPB<br>PPB<br>PPB<br>PPB (6)†<br>PPB<br>HPB | CPP<br>PPP<br>PPP<br>PPP (7)†<br>PPP<br>HPP | PPB<br>PPB<br>PPB<br>PPB (9)†<br>PPB<br>PPB | PPP<br>PPP<br>PPP<br>PPP (10)†<br>PPP<br>PPP |
| 2630B4, 2630C4,<br>2630D4, 2630DA4,<br>2632A4, and<br>2632C4  | PPSS<br>PPSS<br>PPSS (4)<br>PPSS<br>HPSS               |   |   |   |   |  |
| 2630B11, 2630B13,<br>2630C11, 2630C13,<br>2630D11, 2630D13,<br>2630DA11, 2630DA13,<br>2632A11, 2632A13,<br>2632C11, and 2632C13                 | PP OFF<br>PP ON<br>PP T<br>PP V (11)<br>PP<br>HP       | CP OFF<br>PP ON<br>PP T<br>PP V (13)†<br>PP<br>HP |   |   |   |  |
| 2630B12, 2630C12,<br>2630D12, 2630DA12,<br>2632A12, and<br>2632C12  | PSS OFF<br>PSS ON<br>PSS T<br>PSS V (12)<br>PSS<br>HSS |   |   |   |   |  |
| 2630B14, 2630B15,<br>2630C14, 2630C15,<br>2630D14, 2630D15,<br>2630DA14, 2630DA15,<br>2632A14, 2632A15,<br>2632C14, and 2632C15                 | PPLL<br>PPLL<br>PPLL (14)<br>PPLL<br>HPLL              | CPLL<br>PPLL<br>PPLL (15)†<br>PPLL<br>HPLL        |   |   |   |  |

**Notes:**

1. Numerals in parenthesis indicate code of set.
2. Key module arrangements apply to 3-type speakerphone only. For use with 4A speakerphone, refer to Section 512-730-400.

\*All single and double letter coded telephone sets are MD.

†HCPPP-current 635AD5C key configuration with cutoff (first module).

‡Codes not supplied in 2630DA

**Symbols:**

P — Pickup (locking)  
 H — Hold  
 C — Cutoff (turn-locking)  
 SS — Signal  
 B — Blank

T — Transmit  
 V — Volume Control  
 LL — Illuminating Lamp  
 OFF — OFF  
 ON — ON

↓ TABLE J ↓  
**MANUFACTURE DISCONTINUED 2631-TYPE (30-BUTTON) TELEPHONE SET—KEY MODULE AND FACTPLATE ARRANGEMENTS (NOTES)**

| TEL SET CODE *  | KEY CONFIGURATION<br>(NOTE 1)                                      |  |   |  |  |  |  |  |  |                                |  |
|---|--|--|---|--|--|--|--|--|--|--------------------------------|--|
| 2631B1,2,3,10,11,12,13,14,15<br>2631C1,2,3,10,11,12,13,14,15<br>2631D1,2,3,10,11,12,13,14,15<br>2631DA1,2,3,10,11, and 12 | PPPBB<br>PPPBB<br>PPPBB (1)<br>PPPBB<br>HPPBB                      | PPPPB<br>PPPPB<br>PPPPB (2)<br>PPPPB<br>HPPPB                | PPPPP<br>PPPPP<br>PPPPP (3)<br>PPPPP<br>HPPPP | CPPBB<br>PPPBB<br>PPPBB (10)<br>PPPBB †<br>HPPBB | CPPPB<br>PPPPB<br>PPPPB (11)<br>PPPPB †<br>HPPPB | CPPPP<br>PPPPP<br>PPPPP (12)<br>PPPPP †<br>HPPPP | PPPBB<br>PPPBB<br>PPPBB (13)<br>PPPBB ‡<br>PPPBB | PPPPB<br>PPPPB<br>PPPPB (14)<br>PPPPB ‡<br>PPPPB | PPPPB<br>PPPPP<br>PPPPP (15)<br>PPPPP ‡<br>PPPPP | PPPPP (15)<br>‡<br>‡<br>‡<br>‡ |  |
| 2631B4, 2631C4, 2631D4,<br>and 2631DA4  | PPPSS<br>PPPSS<br>PPPSS (4)<br>PPPSS<br>HPPSS                      |  |   |  |  |  |  |  |  |                                |  |
| 2631B16, 2631B17, 2631C16,<br>2631C17, 2631D16, 2631D17,<br>2631DA16 and 2631DA17   | PPPB OFF<br>PPPB ON<br>PPPB T<br>PPPB V (16)<br>PPP<br>HPPB        | PPPP OFF<br>PPPP ON<br>PPPP T<br>PPPP B (17)<br>PPPP<br>HPPP |   |  |  |  |  |  |  |                                |  |
| 2631B18, 2631C18, 2631D18,<br>and 2631DA18  | PPPSS OFF<br>PPPSS ON<br>PPPSS T<br>PPPSS V (18)<br>PPPSS<br>HPPSS |  |   |  |  |  |  |  |  |                                |  |
| 2631D5, and 2631DA5   | PPPSLL<br>PPPSLL<br>PPPSLL (5)<br>PPPSLL<br>HPPSLL                 |  |   |  |  |  |  |  |  |                                |  |
| 2631B9, 2631B19, 2631C9<br>2631C19, 2631D9, 2631D19,<br>2631DA9, and 2631DA19   | PPPBL<br>PPPBL<br>PPPBL (9)<br>PPPBL<br>HPPBL                      | PPPLL<br>PPPLL<br>PPPLL (19)<br>PPPLL<br>HPPLL               |   |  |  |  |  |  |  |                                |  |

**Notes:**

1. Numerals in parenthesis indicate code of set.
2. Key module arrangements apply to 3-type speakerphone only. For use with 4A speakerphone, refer to Section 512-730-400.

\*All 2631-type (single and double letter coded) telephone sets are MD.

†HCPPPP-current 635AD5C key configuration with cutoff (first module).

‡Codes not supplied in 2631DA.

**Symbols:**

P — Pickup (locking)  
 H — Hold  
 C — Cutoff (turn-locking)  
 SS — Signal  
 B — Blank

T — Transmit  
 V — Volume Control  
 LL — Illuminating Lamp  
 OFF — OFF  
 ON — ON