

## 7A COMMUNICATION SYSTEM

### (COM KEY\* 718)

#### 1. GENERAL

**1.001** This addendum supplements Section 518-450-100, Issue 2.

**1.002** This addendum is issued to:

- Rate the 832B, 2832B, 832C and 2832C telephone sets MD and add information on the 832BM, 2832BM, 832CM and 2832CM telephone sets
- Revise Tables G and H.

#### 2. DESCRIPTION OF APPARATUS

The following changes apply to Part 2 of this section:

- (a) Add 2.32.1, 2.32.2, and 2.32.3.

**2.32.1** The 832B, 2832B, 832C and 2832C telephone sets are rated MD and are replaced by the 832BM, 2832BM, 832CM and 2832CM telephone sets, respectively. The 832BM, 2832BM, 832CM and 2832CM telephone sets are of modular design and equipped with a G15A-50 handset and an H4DU-50 handset cord.

**2.32.2** Starting about November 1975, some of the modular 832- and 2832-type telephone sets will be manufactured with a new line switch. The new line switch has an additional set of contacts and an improved ABR feature. There are no changes in the connections for telephone sets having the new line switch, except when used with a speakerphone.

**2.32.3** When using the 3B or 4A speakerphone with a modular 832- or 2832-type telephone set, determine whether or not there is an O lead on terminal 27 of the telephone set terminal board. Where an O lead is on terminal 27, it must be moved to terminal 22. Failure to move this lead will cause the telephone set dial to be inoperative when using the speakerphone.

#### 4. FEATURES (IDENTIFICATION, OPERATION, CONNECTIONS, AND TESTING)

The following changes apply to Part 4 of this section:

- (a) Table G—revised  
(b) Table H—revised

\*Trademark of AT&T Company

#### NOTICE

Not for use or disclosure outside the  
Bell System except under written agreement

TABLE G  
832A AND 2832A TELEPHONE SET CONNECTIONS FOR  
PRIVACY RELEASE BUTTON (D-180488 KIT OF PARTS)

TEL SET LEAD	PRIVACY BOARD LEAD	PRIVACY RELEASE KEY LEADS	CONNECT TO TEL SET TERM.	MOVE LEADS	
				FROM TEL SET TERM.	TO PRIVACY BOARD TERM.
		O-BK	10		
		BK-BL	15		
		G-Y	27		
		Y-G	27		
		G-W	2*		S2
BK			2*	15	S2
	S†			15	S2

\* If telephone set does not have privacy circuit.

† If telephone set has privacy circuit and privacy release is now being added.

TABLE H  
832A AND 2832A TELEPHONE SET CONNECTIONS  
TO DISABLE PRIVACY RELEASE BUTTON

TEL SET LEAD	PRIVACY BOARD LEAD	PRIVACY RELEASE BUTTON LEADS	REMOVE FROM TEL SET TERM.	MOVE LEADS	
				FROM PRIVACY BOARD TERM.	TO TEL SET TERM.
		O-BK	10		
		BK-BL	15		
		G-Y	27		
		Y-G	27		
		G-W	2*	S2	
BK			2*	S2	15
	S†			S2	15

\* If telephone set does not have privacy circuit.

† If telephone set has privacy circuit and privacy release is being removed.